






Embedded MicroBoxes

Selection Guide



Model (W x D x H)	Accessory Specifications			SBC Selections			
	Drive Bay	Expansion Slot	Power Supply	3.5" Capa	5.25" Petit	Half-size	Mini ITX
 EM60323 270 x 260 x 55 mm	1 x 2.5"	N/A	ATX 180 W (50916A24000E) Input: AC 115 - 230V Output: +3.3V @ 3A, +5V @ 16A, +12V @ 5.86A, -12V @ 0.8A, +5Vsb @ 2A ATX 250 W (50986624010E) Input: AC 115 - 230V Output: +3.3V @ 4A, +5V @ 6A, +12V @ 16.5A, -12V @ 0.4A, +5Vsb @ 1A				SBC86831 SBC86832 SBC86822 SBC86840 SBC86841 SBC86860
 EM60322 300 x 273 x 65 mm	1 x 2.5" or 1 x 3.5" Slim CD-ROM x 1	1 x PCI	80 W Adapter with 90W DC open frame AC adapter: 80W Input: AC 100 - 240V Output: 12V @ 5A DC open frame: 90W Input: DC 11.4 - 12.6V Output: +3.3V @ 7A, +5V @ 7A, +12V @ 2A, -12V @ 0.1A, +5Vsb @ 1A				SBC86822
 EM1610 316 x 225 x 51 mm	1 x 2.5"	N/A	AT 100 W (82016100070E) Input: AC 90 - 264V Output: +5V @ 11.5A, +12V @ 3A, -12V @ 0.5A AT 120 W (82016100080E) Input: DC 14 - 32V Output: +5V @ 14A, +12V @ 4A		SBC83810		
 EM16115 225 x 225 x 51 mm	1 x 2.5"	1 x PC104	AT 72 W (50966911000E) Input: AC 90 - 260V Output: +5V @ 10A, +12V @ 1.5A, -12V @ 0.3A AT 72 W (50968911000E) Input: DC 9 - 18V Output: +5V @ 10A, +12V @ 1.5A, -12V @ 0.3A AT 72 W (50967911000E) Input: DC 18 - 36V Output: +5V @ 10A, +12V @ 1.5A, -12V @ 0.3A	SBC84620 SBC84621 SBC84710			
 EM60320C 335 x 250 x 88 mm	1 x 3.5" (Default)	2 x PCI	ATX 180 W (50916A24000E) Input: AC 115 - 230V Output: +3.3V @ 3A, +5V @ 16A, +12V @ 5.86A, -12V @ 0.8A, +5Vsb @ 2A		SBC83810		
 EM60320I 335 x 250 x 88 mm	1 x 3.5" (Default)	2 x PCI or 2 x PCIe	ATX 180 W (50916A24000E) Input: AC 115 - 230V Output: +3.3V @ 3A, +5V @ 16A, +12V @ 5.86A, -12V @ 0.8A, +5Vsb @ 2A ATX 250 W (50986624010E) Input: AC 115 - 230V Output: +3.3V @ 4A, +5V @ 6A, +12V @ 16.5A, -12V @ 0.4A, +5Vsb @ 1A				SBC86831 SBC86832 SBC86822 SBC86840 SBC86841 SBC86836 SBC86860